

Current Restricted Power Supply

I. Product description :

1. This production is designed for special power supply device that won't be damaged due to short circuit within 30 minutes.
2. Rotary button to adjust current.
3. While resistance and voltage decreases, this device keeps current without changing and stable.
4. Do not need concatenate with slide resistors.

II. Product specification :

1. Aluminum case with heat radiation and a powerful fan device.
2. Size : L260mm×W130mm×H95mm.
3. Digital meter: 3 digitals in red, 19 mm x 36 mm monitor.
4. Functional names and warning items are printed on this case. CAUTION : Pay attention to the maximum restricted current to avoid overload and burning the resistance.
5. Power input : Power input please follow up with the mark from actual production. There are two different types of power of AC 110V/60Hz or AC 220V/50Hz. Attached one additional three-pin plug cord.
6. Steady flow output : 0~5A.



III. Product instruction (as shown in the graphic panel) :

1. Output DC contact +/- : DC Output single wire connecting terminal with 4mm aperture .
2. Rotary current adjust button : Current can be adjusted from 0~5A
3. Current in digital meter : Measurement range from 0~10A, minimum scale: 0.1A ◦
4. Power receptacle : Three-pin plug according to actual production power.
5. Main power switch : Power on/off.
6. FUSE: 20mm 1Amp fuse is made of glass tube.